Anapurna M firmware upgrade

Program: dgirip_v1.84.exe

Latest firmware: v1[1].219tn6.bin (for example)

Procedure:

Start Anapurna M with "ESC"-button pressed. Press "F2" button to start the ROM UPDATE.

Run the "dgirip"-program:

BG DGIRIP v1.84	×
RIP File J:\Anapurna M\M firmware upgrade\v1[1].219tn6.	Browse
Printer IP 127 . 0 . 0 . 1 Port 5000	Start
Model ST Series 💌 Mode FINE 💌	Cancel
Direction BI	Exit
RIP File Information	
Size (mm) : Quality :	
Top Margin (mm) : Direction :	
Left Margin (mm) :	
Status	
	0%

Browse... to the bin-file.

Open					?×
Look in: 🔂	M firmware upgrade	• 🗢	* 🖻	:::: •	
DGI dgirip_v1.8	34				
rip.cfg					
Wv1[1].212t	n6 - (
V1[1].218t	n6				
File name:	v1[1].219tn6	 		Oper	
Files of type:	All File (*.*)	-]	Cance	

Insert the correct Printer IP. Press the Start button.

Check the engine screen. After upgrading the engine starts automatically.